

# Intex Lumo® 2500 Lumens (30W) Rechargeable LED Worklight

#### **Product Description:**

Intex LED Work Lights designed for cool non-glare work-site illumination, featuring advanced Chips-On-Board technology to deliver true representation of colours, optimised colour temperature and even beam patterns, improving lighting effect and efficiency.

## **Specifications:**

Code SLB30
Lumens 2500/1250
Run Time 4/8 Hours
Charge Time 4.5 Hours

Voltage AC 100-240 50/60Hz

Battery 7.4V/10.4Ah

Power Cable 5m H05RN 3\*1.0SQmm

Water Resistant Rating IP65
Impact Resistance Rating IK09
Warranty 12 Months

AS/NZS 60598.2.4:2005 Inc A1 - AS/NZS 60598.1:2013 AS/NZS 60598.2.5:2002 - AS/NZS 61347.2.13:2013 - AS/NZS 61347.1:2016

#### **Contents:**

30W LED WorkLight
7.4V/10.4Ah Li-ION Battery Pack
5m H05RN 3\*1.0SQm Cable
Instruction Manual

## **Battery & Power Instructions:**

- Charge battery for at least 8 hours before first use.
- Red indicator on lamp means 'charging in process'.
- Green indicator on lamp means 'charging complete'.
- Always fully charge to extend battery life.
- Do not leave battery in full discharged condition.
- Recharge Work Light at least once in every 30 days.
- Do not charge Work Light if wet or damp.
- Only use original and genuine Intex cords and chargers.

### Warnings:

- Wear safety goggles (user and bystanders).
- Avoid looking directly into light beam.
- Do not use Work Light near open flames.
- Do not cover LED lens when operating, to prevent overheating.
- Do not contaminate LED lens with organic solvents.
- Take care to position Work Light in a careful manner to ensure the light is properly supported by the stand.
- After adjusting Work Light stand angle be sure to tighten the stands adjustment screw.
- When using Work Light at heights take additional precautions to ensure safe use and prevent falling objects causing harm to bystanders and equipment.

